

Please follow the instructions below when setting up the Billion BiPAC 7401VGP with our VoIP service.

1. Log into the web configuration page of the BiPAC 7401VGP.

**URL:** 192.168.1.254

**Default Username:** admin

**Default Password:** admin


2. Click on **Configuration -> VoIP**
3. Do not click on Wizard straight away please open up **General Settings**
4. Change the following settings on the page that comes up with the settings that are provided with your settings sheet.

**Region:** Australia

**Registrar Address:** sip.isage.net.au

**User Domain/Realm:** sip.isage.net.au

**Outbound Proxy Address:** sip.isage.net.au



5. Click on Apply
6. Now go to the Wizard Page
7. On this page enter the following details as per your setup sheet:

**SIP Service Provider:** Select the bottom provider should match the Proxy Registration Info on your settings sheet.

**Phone Number:** VoIP Service Number

**Authentication Username:** VoIP Username

**Authentication Password:** VoIP Password



8. Click on Apply
9. Click on Save Configuration to Flash (on the left hand side menu)

10. Select to save current configuration and reboot

Once the device restarts you are now ready to start using your iSage VoIP service.